

# DHI-ARD512-W2

Dahua Wireless Glass Break Detector



## System Overview

The Wireless Glass Break Detector recognizes when different types of glass are breaking, triggering alarms in real time. With its advanced technology, it picks up the low-frequency and high-frequency that glass breaks at, reducing the occurrence of false alarms caused by noise interference from the environment. It also comes with 2 external ports that can connect to third-party wired detectors. When placed in a home or building, it helps protect families and work places from intrusions.

### **Technical Specification**

#### Port


| Alarm Input                               | 2 (NO/NC)   |
|---|---|
| Microphone                                | Highly-sensitive omnidirectional microphone   |
| Function                                  |   |
| Button                                    | 1 × power button  |
| Remote Update                             | Cloud update  |
| Low Battery Detection                     | Yes   |
| Tamper                                    | Yes   |
| Technical                                 |   |
| Detection Range                           | Max. 9 m (29.53 ft)   |
| Specifications of Glass to be<br>Detected | Glass type: Tempered, double-glazed, laminated,<br>wired, plate and float<br>Glass thickness: 2.4 mm–6.4 mm (0.09"–0.25")<br>Glass size: 0.3 m × 0.3 m to 3 m × 3 m (0.98 ft × 0.98 ft<br>to 9.84 ft × 9.84 ft) |
| Test Mode                                 | Yes   |
| LED Indicator                             | 1 × green alarm indicator   |
| Scenario                                  | Indoor  |
| Operating Current                         | 45 uA   |
| Alarm Current                             | 50 mA   |

- Detects when the glass is broken, triggering alarms for different types of glass such as tempered, double-glazed, laminated, wired, plate and float glass.
- Detects high and low frequency sounds at the same time, and uses algorithms to reduce the occurrence of false alarms.
- · Two-channel alarm input.
- · Cloud update and automatic recovery from update failure.
- The two-way wireless encrypted communication mechanism improves the security and stability of communication.
- With the wireless frequency hopping mechanism, the device automatically hops to other available frequency bands when the original frequency band is being interfered with by other wireless radios, to ensure communication remains stable.


#### Wireless

| Carrier Frequency       | 433.1 MHz-434.6 MHz  |
|-------------------------|--|
| Communication Mechanism | Two-way  |
| Communication Distance  | 1,200 m (3,937.01 ft)  |
| Encryption Mode         | AES128   |
| Frequency Hopping       | Yes  |
| General                 |  |
| Power Supply            | 1 × CR123A battery   |
| Battery Model           | CR123A   |
| Battery Life            | 3 years (The external input type is NO)<br>1 year (Both external sensors are enabled, and the<br>input type is NC) |
| Power Consumption       | Max. 150 mW  |
| Operating Temperature   | –10 °C to +55 °C (+14 °F to +131 °F) (indoor)  |
| Operating Humidity      | 10%–90% (RH)   |
| Product Dimensions      | 107.8 mm × 34.5 mm × 24.8 mm (4.24" × 1.36" × 0.98")   |
| Net Weight              | 45 g (0.10 lb)   |
| Gross Weight            | 130 g (0.29 lb)  |
| Installation            | Surface mount  |
| Casing Material         | PC and ABS   |
| Appearance Color        | White  |
| Certifications          | CE   |
| Anti-corrosion Level    | Basic Protection   |
| Packaging Dimensions    | 95 mm × 43 mm × 139 mm (3.74" × 1.69" × 5.47")   |
|                         |  |


## Installation



## Dimensions (mm/inch)



## Application



Rev 002.000 © 2023 Dahua. All rights reserved. Design and specifications are subject to change without notice. The images, specifications and information mentioned in the document are only for reference, and might differ from the actual product.